



TIG SERIES



MMA



• Specifications

Products Type	TIG 500 IJ
Model	RT50
Input Voltage (V)	AC 415 ± 15%
Rated Input Current (A)	26.2/35.0
Power (KVA)	25.2
No-load Voltage (V)	70
Output Current (A)	10-500
Rated Output Voltage (V)	38
Duty Cycle (%)	60
No-load Loss (W)	80
Efficiency (%)	85
Power Factor	0.93
Pre-Flow (Sec.)	2.5
Post-Flow (Sec.)	0-5
Arcing Way	High Frequency
Net Weight (Kg)	42
MMA Function	Available
Inverter Technology	IGBT

• Features

- High Frequency ignition
- Superior arc performance
- Post-flow function
- Light and compact, easy to carry and use
- Economises tungsten use with a stable output & high duty cycle

• Standard Accessories



* In view of continuous development RALLIWOLF reserves the right to modify / alter the design / modification without prior notice

Ralli Wolf Industries Ltd.

(Formerly Ralli Engineering Ltd)

An ISO 9001 : 2015 certified Organisation

Regd. Office : 4, Fairlie Place Kolkata - 700001 (India), E : info@ralliwolf.com, P : +91 33 2262 7341

SALES NETWORK : Ahmedabad | Akola | Baroda | Bangalore | Bhubaneswar | Bhopal | Chennai | Coimbatore | Cuttack | Delhi
Faridabad | Guwahati | Indore | Jaipur | Jamshedpur | Kolkata | Ludhiana | Mumbai | Nagpur | Pune | Raipur | Secunderabad | Trichy